

Axial space saving structure and precise guided type

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2

Axial space saving

Compact axial length
Footprint reduced


Long service life design (approximate 4 times (CKD comparison))

Oil impregnated copper bearing at rod bearing dramatically improves abrasion resistance.


Optional piping direction is available

The piping can be selected from 2 way of main body side or main body bottom surface.

● MSDG



● MSD



Miniature type with switch F series installation.

6, 8 mm bore compact size with switch is available.

Direct 3-surface mount



Square body enables direct mount on any cylinder surfaces. Through bolts or top installation is possible from top or bottom side. Common rear port enables sideways installations.

High precision, high rigidity and space saving
High precision guided

MSDG Series

Axial space saving structure and guided type

High precision guide is installed on short axial length MSD series.
Meets high precision/high rigidity needs even in narrow space.



In addition to conventional compact cylinders, 6 and 8 mm bore compact cylinder MSD series is now available. High precision guide is integrated into compact body.



SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Small compact cylinder
Space saving structure

6, 8 mm bore compact cylinder debut.

MSD Series

Axial space saving is realized



SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

●: Standard, ○: Option, ■: Not available


Variation	Model no.	Bore size (mm)	Standard stroke length (mm)						Min. stroke length (mm)	Max. stroke length (mm)	Option		Switch	Page
			5	10	15	20	25	30			Rear common port	R		
Double acting single rod type with switch	MSD MSD-L	φ6, φ8	●	●	●	●	●	●	5	30	○	○	○	1048
Single acting extend type with switch	MSD-X MSD-XL	φ6, φ8	●	●					5	10	○	○	○	1056
Single acting retract type with switch	MSD-Y MSD-YL	φ6, φ8	●	●					5	10	○	○	○	1056
Double acting high load type with switch	MSD-K MSD-KL	φ6, φ8 φ12, φ16	●	●	●	●	●	●	5	30	○	○	○	1066
Double acting single rod type fine speed type with switch	MSD-F MSD-LF	φ6, φ8	●	●	●	●	●	●	5	30			○	1076
High load type fine speed type with switch	MSD-KF MSD-KLF	φ6, φ8 φ12, φ16	●	●	●	●	●	●	5	30			○	1076
Double acting guided	MSDG-L	φ6, φ8 φ12, φ16	●	●	●	●	●	●	5	30	○	○	○	1078
Double acting guided fine speed type	MSDG-LF	φ12, φ16	●	●	●	●	●	●	5	30	○	○	○	1088

MSD/MSDG Series


Major applications

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending


Selection of passed/rejected products




Clamp



Positioning of pallet/stopper




Transfer of workpiece




Note: When using as a stopper, consult with CKD.

Pin hole used positioning



Compact part feed



Variation and option selection table

● MSD Series

○ : Option
 ◎ : Available (custom order)
 △ : Available depending on condition (consult CKD)
 X : Not available

Code	Code	Variation		Port thread	Option							
		No	Symbol	Double acting single rod type	High load type	Single acting extend type	Single acting retract type	With cylinder switch	Fine speed type	NPT	G	Rear common port
Variation	Double acting single rod type	Blank		X	X	X	X	X	X	X	X	◎
	High load type	K		X	X	◎	◎	X	X			◎
	Single acting extend type	X		X	○	X	X	X				○
	Single acting retract type	Y			○	X	X	X				○
	With cylinder switch	L				○	X	X				○
	Fine speed type	F					X	X				○
Port thread	NPT	N						X		X		
	G	G									X	
Accessory	Rear common port	R										
	Cylinder switch	Listed on Ending	○	○	○	○	○	○	X	X	○	

● Guided type MSDG Series

○ : Option
 ◎ : Available (custom order)
 △ : Available depending on condition (consult CKD)
 X : Not available

Code	Code	Variation		Port thread	Option			
		No	Symbol	Double acting single rod type	Fine speed type	NPT	G	Rear common port
Variation	Double acting single rod type	Blank		X	X		○	
	Fine speed type	F		X	X		○	
	NPT	N			X	X		
	G	G				X		
	Rear common port	R						
	Cylinder switch	Listed on Ending	○	○	X	X	○	

SCP*2

CMK2

CMA2

SCM

SCG

SCA2

SCS

CKV2

CA/OV2

SSD

CAT

MDC2

MVC

SMD2

MSD*

FC*

STK

ULK*

JSK/M2

JSG

JSC3

USSD

USC

JSB3

LMB

STG

STS/L

LCS

LCG

LCM

LCT

LCY

STR2

UCA2

HCM

HCA

SRL2

SRG

SRM

SRT

MRL2

MRG2

SM-25

CAC3

UCAC

RCC2

MFC

SHC

GLC

Ending

Small compact cylinder
Space saving structure

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2



Pneumatic components Safety precautions

Always read this section before starting use.

Refer to Intro 71 for general details on the cylinder, and to Intro 78 for details on the cylinder.

Small compact cylinder MSD/MSDG Series

Design & Selection

1. Common

⚠ CAUTION

- Follow "Selection guide" on page 1090, when selecting the cylinder.
- When using this cylinder as a stopper, consult with CKD.
- When selecting cylinder switch, refer to "Switch selection table" on page 1059.
- When installation, switch tightening torque should be observed.
In exceeding tightening torque range, a setscrew, a mounting bracket and a switch etc. may be damaged. While insufficient tightening torque may cause a misallocation of switch.
Tightening torque: 29.4 (N.mm)

2. Single acting MSD-X/Y

⚠ CAUTION

- Do not use the extending type if a load is applied when the piston rod is retracted, and do not use the retracting type if a load is applied when the position rod is extending.
The cylindrical spring in the cylinder does not have power to return the piston rod, so if a load is applied, the piston rod will not return to the stroke end.
- This cylinder has a bleed hole which must not be covered when the cylinder is mounted.
Operation faults could occur if the bleed hole is covered.
- Do not leave the single acting cylinder in the pressurized state.
If left pressurized, the piston rod may not return with spring power when pressure is released.


3. Fine speed type MSD-(K) F/MSDG-LF

⚠ CAUTION

- Use with oil-free specifications.
Lubrication may change characteristics.
- Assemble the flow control valve near the cylinder.
Adjustments become unstable if assembled away from the cylinder. Use the SC-M3/M5, SC3W, SCD-M3/M5, SC3WU Series speed control valve.

■ Generally, the higher air pressure, and the smaller load pressure result in the more stable operation.
Keep the load factor at 50% or less.


■ Stable speed control is achieved with a meter-out circuit.
When driving the single rod cylinder at fine speed with the operation direction set to PUSH, popping-out may occur if operation is started when load resistance is small. As a countermeasure, use (b), (c), or (d) circuit. Note that the (d) circuit is the most stable.




① Speed adjustment method at PUSH operation circuit
1. Set the speed with the x speed control valve
2. Lower the flow rate with the y speed control valve until popping out no longer occurs
3. Reconfirm of velocity

(Note 1) As comparing (b), (c) and (d), circuit (d) is most stable.

(Note 2) When vertical installation, a meter-in circuit results in falling by its self-weight. So, provide a meter-out circuit.



(Note 3) For serial connection of speed control valve, provide a circuit as the following diagram.



(Cause of popping out)

Reduce the flow rate to reach a fine speed at the exhaust side in a meter-out circuit. This results in the same pressure level on the both sides immediately after valve switched. The thrust caused by the differential of pressurized area of piston is applied to the PUSH direction and a popping-out of piston rod occurs.

(Guide for popping out occurrence)

Popping out occurs when: the piston rod area \times air pressure > load resistance.

■ Do not apply lateral load a cylinder.

Install the cylinder to avoid the sliding guide to be twisted.

The presence of load or resistance variation may result in unstable operations. Operation of a guide having a large difference in stationary and moving friction may become unstable.

■ Avoid use with vibration.

The product will be adversely affected by vibration and operation will be unstable.

Installation & Adjustment


1. Common

▲ CAUTION

■ Piping

Cautions for piping, speed control and joint

Applicable piping joints are limited, so refer to the table below.



Joint selection table

Symbol Bore size (mm)	Port size	Port dimension A	Applicable speed control valve, joint	Joint O.D.
φ6 φ8	M3	4	SC3W-M3-3 SC3W-M3-4 SC3WU-M3-3 SC3WU-M3-4 GWS3-M3-S GWS4-M4-S FTS4-M3	φ 8 or less
φ12 φ16	M5	5	SC3W-M5-3 SC3W-M5-4 SC3W-M5-6 SC3WU-M5-3 SC3WU-M5-4 SC3WU-M5-6 GWS4-M5-S GWS6-M5-S FTS4-M5 FTS6-M5	φ 10 or less

■ Installation

Do not damage the main body (cylinder tube) fixing surface and the table surface with dent or scratch etc., which are harmful to flatness. The flatness of object installed onto the table should be 0.05mm or less.

2 Fine speed type MSD-KF/MSDG-LF

▲ CAUTION

■ Adjust the core, etc., so lateral load is not applied to the cylinder.

Adjust and install so the sliding guide is not twisted.

The presence of load or resistance variation may result in unstable operations. Operation of a guide having a large difference in stationary and moving friction may become unstable.

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending




Small compact cylinder, double acting single rod type

MSD Series

● Bore size: $\phi 6, \phi 8$

JIS symbol



Specifications

Descriptions		MSD MSD-L (with switch)
Bore size	mm	$\phi 6, \phi 8$
Actuation		Double acting
Working fluid		Compressed air
MSD*	Max. working pressure MPa	1.0
FC*	Min. working pressure MPa	0.15
STK	Withstanding pressure MPa	1.6
ULK*	Ambient temperature °C	-10 to 60 (no freezing)
JSK/M2	Port size	M3
JSG	Stroke tolerance mm	+0.5 0
JSC3	Working piston speed mm/s	50 to 500
USSD	Lubrication	Not required (when lubricating, use turbine oil ISO VG32.)

Stroke length

Bore size (mm)	Standard stroke length (mm)	Max. stroke length (mm)	Min. stroke length with 2 switches (mm)		Min. stroke length with 1 switch (mm)	
			Reed switch	Proximity switch	Reed switch	Proximity switch
$\phi 6$	5, 10, 15, 20, 25, 30	30	10	5	5	5
$\phi 8$	5, 10, 15, 20, 25, 30	30	10	5	5	5

Note: Other than standard stroke length is not available.

Switch specifications

Descriptions	Reed 2 wire	Proximity 2 wire	Proximity 3 wire		
	F0H/V	F2H/V	F3H/V		
Applications	Programmable controller		Programmable controller, relay		
Output method	-		NPN output		
Power voltage	-		10 to 28 VDC		
Load voltage	24 VDC	10 to 30 VDC	30 VDC or less		
Load current	5 to 20mA (Note 1)	5 to 20mA (Note 1)	50mA or less		
Current consumption	-	-	(When turned ON) 10mA or less with 24 VDC		
Internal voltage drop	4V or less		0.5V or less		
Light	Yellow LED (ON lighting)				
Leakage current	1mA or less		10 μ A or less		
Lead wire length (standard)	Standard 1m (oil resistant vinyl cabtire code 2 conductor 0.15mm ²)		Standard 1m (oil resistant vinyl cabtire code 3 conductor 0.15mm ²)		
Maximum shock resistance	294m/s ²	980m/s ²			
Insulation resistance	20 M Ω and over with 500 VDC megger				
Withstand voltage	No failure at 1000 VAC for one minute.				
Ambient temperature	-10 to + 60 °C				
Protective structure	IEC standards IP67, JIS C 0920 (water tight type), oil resistance				

Note 1: Max. load current 20mA is the value at 25 °C.

The current will be lower than 20mA if ambient temperature around switch is higher than 25°C.
(5 to 10mA at 60 °C)

Cylinder weight table

Stroke length (mm)	5		10		15		20		25		30		(g) Weight per 1 switch
Bore size (mm)	W/o switch	With switch											
φ6	22	24	25	27	27	29	30	32	33	35	36	38	10
φ8	23	26	28	31	33	36	38	41	42	45	47	50	

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Small compact cylinder
Space saving structure

MSD Series

How to order

- Without switch

MSD - **6** - **5** - **R**

- With switch

MSD-L - **6** - **5** - **F0H** - **R** - **R**

A Model no.

B Bore size

C Stroke length

D Switch model no.
Note 1

E Switch quantity

F Piping port position
Note 2

Symbol	Descriptions	
A Model no.	MSD Double acting MSD-L single rod type	Without switch
		With switch

Symbol	Bore size (mm)	
B	6	φ6
	8	φ8

Symbol	C Stroke length (mm)	
C	5	5
	10	10
	15	15
	20	20
	25	25
	30	30

Symbol	D Switch model no.				
	Axial lead wire	Radial lead wire	Contact	Indicator	Lead wire
F0H*	F0V*	Reed		1 color indicator type	2-wire
F2H*	F2V*		Proximity		
F3H*	F3V*				3-wire

*Lead wire length

Blank	1m (standard)
3	3m (option)

Symbol	E Switch quantity	
R	1 on rod end	
H	1 on head end	
D	Two	

Symbol	F Piping port position	
Blank	Body side surface port	
R	Rear common port	

⚠ Note on model no. selection

Note 1: For 6, 8 mm bore cylinders with switches, use mounting bolts that do not contain magnetic substances (stainless steel etc.).

Note 2: For rear common port type, a side installation is possible. In this case, two bolts are used for head or rod side installation.

<Example of model number>

MSD-L-6-5-F0H-R-R

- A** Model no. : Double acting single rod type with switch
- B** Bore size : φ6mm
- C** Stroke length : 5mm
- D** Switch model no. : Reed F0H, lead wire 1m
- E** Switch quantity : 1 on rod end
- F** Option : Rear common port

How to order switch


SW - **F0H**

Switch model no.
(Item **D** above)


Switch selection table

Switches could not be installed depending on relations between cylinder installation and stroke length.
Refer to the table below to select a switch.


All switches can be used when side installation. (Refer to page 1048 for min. stroke length with switch)



(R) Rod end installation



(H) Head end installation



Side installation

● Rod end installation

Bore size (mm)	Stroke length (mm)	Reed switch				Proximity switch			
		F0H		F0V		F2H/F3H		F2V/F3V	
		Switch installation position	R	H	R	H	R	H	R
$\phi 6$	5	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	15 to	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
$\phi 8$	5	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	15 to	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>

● Head end installation

Bore size (mm)	Stroke length (mm)	Reed switch				Proximity switch			
		F0H		F0V		F2H/F3H		F2V/F3V	
		Switch installation position	R	H	R	H	R	H	R
$\phi 6$	5	<input checked="" type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	15 to	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
$\phi 8$	5	<input checked="" type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	15 to	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Small compact cylinder
Space saving structure

MSD Series

Internal structure and parts list

SCP*2

CMK2

CMA2

SCM

SCG

SCA2

SCS

CKV2

CA/OV2

SSD

CAT

MDC2

MVC

SMD2

MSD*

FC*

STK

ULK*

JSK/M2

JSG

JSC3

USSD

USC

JSB3

LMB

STG

STS/L

LCS

LCG

LCM

LCT

LCY

STR2

UCA2

HCM

HCA

SRL2

SRG

SRM

SRT

MRL2

MRG2

SM-25

CAC3

UCAC

RCC2


MFC

SHC


GLC

Ending

● MSD-6, 8



● MSD-L-6, 8




No.	Parts name	Material	Remarks	No.	Parts name	Material	Remarks
1	Piston	Stainless steel		6	Piston packing seal	Nitrile rubber	
2	Bush	Oil impregnated copper alloy		7	Magnet	Plastic	
3	Hexagon socket head set screw	Stainless steel		8	E type snap ring	Stainless steel	
4	Rod packing seal	Nitrile rubber		9	Body	Aluminum alloy	Hard alumite
5	Rod bushing	Stainless steel					


Dimensions



● MSD- (L)-6, 8



● MSD- (L)-6, 8-*R (rear common port)



Bore size (mm)	Without switch		With switch		Without switch/common dimension with switch											
	A	B	A	B	C	D	EE	EF	F	GA	GB	HH	I	J	K	KA
φ6	17.5	14.5	22.5	19.5	7.5	4	M3	M3	19	3	8.5	M3 depth 3	3.2	Spot face φ6.1 depth 3.5	22.5	M4 depth 6
φ8	19	16	24	21	9	4	M3	M3	21	4.5	8.5	M3 depth 3	3.2	Spot face φ6.1 depth 3.5	25	M4 depth 6

Bore size (mm)	Without switch/common part with switch				
	KK	M	MM	N	X
φ6	M2.5 depth 4	3.5	4	11	3
φ8	M3 depth 5	4.5	5	12.5	3


SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Small compact cylinder
Space saving structure

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Switch installation position

● Switch installation position



● Switch installation position dimension

(mm)

Model	Bore size (mm)	Reed switch				Proximity switch			
		F0H		F0V		F2H/F3H		F2V/F3V	
		RD	HD	RD	HD	RD	HD	RD	HD
MSD-L	φ6	3.5	3.5	3.5	0.0	7.5	1.5	7.5	1.5
	φ8	5.5	4.0	5.5	0.0	9.5	1.0	9.5	1.0



Small compact cylinder, single acting extend type/with switch
single acting retract type/with switch

MSD-X Series

● Bore size: $\phi 6$, $\phi 8$

JIS symbol



Single acting extend type Single acting retract type



Specifications

Descriptions		MSD-X MSD-XL (with switch)		MSD-Y MSD-YL (with switch)		
Bore size	mm	$\phi 6$	$\phi 8$	$\phi 6$	$\phi 8$	
Actuation	Single acting extend type			Single acting retract type		
Working fluid	Compressed air					
Max. working pressure	MPa	1.0				
Min. working pressure	MPa	0.3		0.4	0.3	
Withstanding pressure	MPa	1.6				
Ambient temperature	°C	-10 to 60 (no freezing)				
Port size	M3					
Stroke tolerance	mm	$+0.5$		0		
Working piston speed	mm/s	50 to 500				
Lubrication	Not required (when lubricating, use turbine oil ISO VG32.)					

Stroke length

Bore size (mm)	Standard stroke length (mm)	Max. stroke length (mm)	Min. stroke length with 2 switches (mm)		Min. stroke length with 1 switch (mm)	
			Reed switch	Proximity switch	Reed switch	Proximity switch
$\phi 6$	5, 10	10	10	5	5	5
$\phi 8$	5, 10	10	10	5	5	5

Note: Other than standard stroke length is not available.

Switch specifications

Descriptions	Reed 2 wire	Proximity 2 wire	Proximity 3 wire		
	F0H/V	F2H/V	F3H/V		
Applications	Programmable controller		Programmable controller, relay		
Output method	-		NPN output		
Power voltage	-		10 to 28 VDC		
Load voltage	24 VDC	10 to 30 VDC	30 VDC or less		
Load current	5 to 20mA (Note 1)	5 to 20mA (Note 1)	50mA or less		
Current consumption	-	-	(When turned ON) 10mA or less with 24 VDC		
Internal voltage drop	4V or less		0.5V or less		
Light	Yellow LED (ON lighting)				
Leakage current	1mA or less		$10\mu A$ or less		
Lead wire length (standard)	Standard 1m (oil resistant vinyl cabtire code 2 conductor 0.15mm ²)		Standard 1m (oil resistant vinyl cabtire code 3 conductor 0.15mm ²)		
Maximum shock resistance	294m/s ²	980m/s ²			
Insulation resistance	20MΩ and over with 500 VDC megger				
Withstand voltage	No failure at 1000 VAC for one minute.				
Ambient temperature	-10 to + 60°C				
Protective structure	IEC standards IP67, JIS C 0920 (water tight type), oil resistance				

Note 1: Max. load current 29mA is the value at 25 °C.

The current will be lower than 20mA if ambient temperature around switch is higher than 20mA.
(5 to 10mA at 60 °C)

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Cylinder weight table

● MSD-X/MSD-XL

Stroke length (mm)	5		10		Weight per 1 switch
Bore size (mm)	W/o switch	With switch	W/o switch	With switch	
φ6	23	25	28	30	10
φ8	24	27	33	36	

● MSD-Y/MSD-YL

Stroke length (mm)	5		10		Weight per 1 switch
Bore size (mm)	W/o switch	With switch	W/o switch	With switch	
φ6	25	27	31	33	10
φ8	28	31	38	41	

MSD-X/Y spring load

(N)

Bore size (mm)	Stroke length (mm)	Spring load	
		When setting	Operation
φ6	5	1.59	4.90
	10		
φ8	5	3.19	6.86
	10		

MSD-X Series

How to order

- Without switch

MSD-X - 6 - 5 - R

- With switch

MSD-XL - 6 - 5 - F0H - R - R

A Model no.



B Bore size

C Stroke length

D Switch model no.
Note 1

E Switch quantity

F Piping port position
Note 2

Symbol	Descriptions	
A Model no.		
MSD-X	Single acting extend type	Without switch
MSD-Y	Single acting retract type	
MSD-XL	Single acting extend type	With switch
MSD-YL	Single acting retract type	

B Bore size (mm)	
6	φ6
8	φ8

C Stroke length (mm)	
5	5
10	10

D Switch model no.				
Axial lead wire	Radial lead wire	Contact	Indicator	Lead wire
F0H*	F0V*	Reed	1 color indicator type	2-wire
F2H*	F2V*	Proximity		3-wire
F3H*	F3V*			

*Lead wire length

Blank	1m (standard)
3	3m (option)

E Switch quantity	
R	1 on rod end
H	1 on head end
D	Two

F Piping port position	
Blank	Body side surface port
R	Rear common port

⚠ Note on model no. selection

Note 1: For 6, 8 mm bore cylinders with switches, use mounting bolts that do not contain magnetic substances (stainless steel etc.).

Note 2: For rear common port type, a side installation is possible. In this case, two bolts are used for head or rod side installation.

<Example of model number>

MSD-XL-6-5-F0H-R-R

- A Model no. : Single acting extend type with switch
- B Bore size : φ6mm
- C Stroke length : 5mm
- D Switch model no. : Reed F0H, lead wire 1m
- E Switch quantity : 1 on rod end
- F Option : Rear common port

How to order switch


SW - F0H

Switch model no.
(Item D above)


Switch selection table

Switches could not be installed depending on relations between cylinder installation and stroke length.
Refer to the table below to select a switch.


All switches can be used when side installation. (Refer to page 1056 for min. stroke length with switch)



(R) Rod end installation



(H) Head end installation



Side installation

● MSD-XL Rod end installation

Bore size (mm)	Stroke length (mm)	Reed switch				Proximity switch			
		F0H		F0V		F2H/F3H		F2V/F3V	
		Switch installation position	R	H	Switch installation position	R	H	Switch installation position	R
$\phi 6$	5	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
$\phi 8$	5	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>

● MSD-XL Head end installation

Bore size (mm)	Stroke length (mm)	Reed switch				Proximity switch			
		F0H		F0V		F2H/F3H		F2V/F3V	
		Switch installation position	R	H	Switch installation position	R	H	Switch installation position	R
$\phi 6$	5	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
$\phi 8$	5	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>

● MSD-YL Rod end installation

Bore size (mm)	Stroke length (mm)	Reed switch				Proximity switch			
		F0H		F0V		F2H/F3H		F2V/F3V	
		Switch installation position	R	H	Switch installation position	R	H	Switch installation position	R
$\phi 6$	5	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
$\phi 8$	5	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>

● MSD-YL Head end installation

Bore size (mm)	Stroke length (mm)	Reed switch				Proximity switch			
		F0H		F0V		F2H/F3H		F2V/F3V	
		Switch installation position	R	H	Switch installation position	R	H	Switch installation position	R
$\phi 6$	5	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
$\phi 8$	5	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Small compact cylinder
Space saving structure

Internal structure and parts list

SCP*2

CMK2

CMA2

SCM

SCG

SCA2

SCS

CKV2

CA/OV2

SSD

CAT

MDC2

MVC

SMD2

MSD*

FC*

STK

ULK*

JSK/M2

JSG

JSC3

USSD

USC

JSB3

LMB

STG

STS/L

LCS

LCG

LCM

LCT

LCY

STR2

UCA2

HCM

HCA

SRL2

SRG

SRM

SRT

MRL2

MRG2

SM-25

CAC3

UCAC

RCC2


MFC

SHC


GLC

Ending

● MSD-X-6, 8




● MSD-XL-6, 8




No.	Parts name	Material	Remarks	No.	Parts name	Material	Remarks
1	Piston	Stainless steel		6	Piston packing seal	Nitrile rubber	
2	Bush	Oil impregnated copper alloy		7	Magnet	Plastic	
3	Hexagon socket head set screw	Stainless steel		8	E type snap ring	Stainless steel	
4	Rod bushing	Stainless steel		9	Body	Aluminum alloy	Hard alumite
5	Coil spring	Steel	Electrode position coating				

Internal structure and parts list

● MSD-Y-6, 8



● MSD-YL-6, 8



No.	Parts name	Material	Remarks	No.	Parts name	Material	Remarks
1	Piston	Stainless steel		6	Piston packing seal	Nitrile rubber	
2	Bush	Oil impregnated copper alloy		7	Magnet	Plastic	
3	Hexagon socket head set screw	Stainless steel		8	Spring holder	Stainless steel	
4	Rod packing seal	Nitrile rubber		9	Coil spring	Steel	Electrode position coating
5	Rod bushing	Stainless steel		10	Body	Aluminum alloy	Hard alumite



SCP*2
 CMK2
 CMA2
 SCM
 SCG
 SCA2
 SCS
 CKV2
 CA/OV2
 SSD
 CAT
 MDC2
 MVC
 SMD2
MSD*
 FC*
 STK
 ULK*
 JSK/M2
 JSG
 JSC3
 USSD
 USC
 JSB3
 LMB
 STG
 STS/L
 LCS
 LCG
 LCM
 LCT
 LCY
 STR2
 UCA2
 HCM
 HCA
 SRL2
 SRG
 SRM
 SRT
 MRL2
 MRG2
 SM-25
 CAC3
 UCAC
 RCC2
 MFC
 SHC
 GLC
 Ending

Small compact cylinder
 Space saving structure



Dimensions



● MSD-X (L)-6, 8



● MSD-X (L)-6, 8-* -R (rear common port)




Symbol	Without switch		With switch		Without switch/common dimension with switch																
	A	B	A	B	C	D	EE	EF	F	GA	GB	HH	I	J	K	KA	KK	M	MM	N	X
$\phi 6$	5	22.5	19.5	27.5	24.5	7.5	4	M3	M3	19	3	8.5	M3 depth 3	3.2	22.5	M4 depth 6	M2.5 depth 4	3.5	4	11	3
	10	32.5	29.5	37.5	34.5																
$\phi 8$	5	24	21	29	26	9	4	M3	M3	21	4.5	8.5	M3 depth 3	3.2	25	M4 depth 6	M3 depth 5	4.5	5	12.5	3
	10	34	31	39	36																


Dimensions



● MSD-Y (L)-6, 8



● MSD-Y (L)-6, 8-*R (rear common port)



SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending


Small compact cylinder
Space saving structure

Symbol	Without switch		With switch		Without switch/common dimension with switch																	
	A	B	A	B	C	D	EE	EF	F	GA	GB	HH	I	J	K	KA	KK	M	MM	N	X	
Bore size (mm)	A	B	A	B	C	D	EE	EF	F	GA	GB	HH	I	J	K	KA	KK	M	MM	N	X	
	5	32.5	24.5	37.5	29.5	7.5	4	M3	M3	19	3	8.5	M3 depth 3	3.2	Spot face $\phi 6.1$ depth 3.5	22.5	M4 depth 6	M2.5 depth 4	3.5	4	11	8
$\phi 6$	10	47.5	34.5	52.5	39.5																	13
	5	34	26	39	31																	13
$\phi 8$	10	49	36	54	41	9	4	M3	M3	21	4.5	8.5	M3 depth 3	3.2	Spot face $\phi 6.1$ depth 3.5	25	M4 depth 6	M3 depth 5	4.5	5	12.5	8
																						13

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Switch installation position

● MSD-XL switch installation position




● Switch installation position dimension

Bore size	Stroke length	Switch model no. Max. sensitive position	Reed switch				Proximity switch				(mm)	
			F0H		F0V		F2H/F3H		F2V/F3V			
			RD	HD	RD	HD	RD	HD	RD	HD		
MSD-XL	φ 6	5	4.0	4.0	4.0	0	7.5	1.5	7.5	1.5		
		10	9.0	4.0	9.0	0	12.5	1.5	12.5	1.5		
	φ 8	5	5.5	4.0	5.5	0	9.0	1.5	9.0	1.5		
		10	10.5	4.0	10.5	0	14.0	1.5	14.0	1.5		

Switch installation position

● MSD-YL switch installation position



● Switch installation position dimension

	Bore size	Stroke length	Max. sensitive position	(mm)							
				Reed switch				Proximity switch			
				F0H		F0V		F2H/F3H		F2V/F3V	
MSD-YL	φ6	5		RD	HD	RD	HD	RD	HD	RD	HD
		10		3.5	2.5	3.5	2.5	8.0	7.0	8.0	7.0
	φ8	5		5.5	2.0	5.5	2.0	10.0	6.0	10.0	6.0
		10		5.5	7.0	5.5	7.0	10.0	11.0	10.0	11.0

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Small compact cylinder
Space saving structure




Small compact cylinder, double acting high load type

MSD-K Series

● Bore size: $\phi 6, \phi 8, \phi 12, \phi 16$

JIS symbol



SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2

SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Specifications

Descriptions		MSD-K MSD-KL (with switch)						
Bore size	mm	$\phi 6$	$\phi 8$	$\phi 12$	$\phi 16$			
Actuation	Double acting							
Working fluid	Compressed air							
Max. working pressure MPa	1.0							
Min. working pressure MPa	0.15		0.1					
Withstanding pressure MPa	1.6							
Ambient temperature °C	-10 to 60 (no freezing)							
Connection	Body side surface port	M3	M5					
Port size	Rear common port	M3	M3					
Stroke tolerance mm	$+2.0$ 0							
Working piston speed mm/s	50 to 500							
Lubrication	Not required (when lubricating, use turbine oil ISO VG32.)							

Stroke length

Bore size (mm)	Standard stroke length (mm)	Max. stroke length (mm)	Min. stroke length with 2 switches (mm)		Min. stroke length with 1 switch (mm)	
			Reed switch	Proximity switch	Reed switch	Proximity switch
$\phi 6$	5, 10, 15, 20, 25, 30	30	10	5	5	5
$\phi 8$	5, 10, 15, 20, 25, 30	30	10	5	5	5
$\phi 12$	5, 10, 15, 20, 25, 30	30	10	5	5	5
$\phi 16$	5, 10, 15, 20, 25, 30	30	10	5	5	5

Note: Other than standard stroke length is not available.

Switch specifications

Descriptions	Reed 2 wire	Proximity 2 wire	Proximity 3 wire		
	F0H/V	F2H/V	F3H/V		
Applications	Programmable controller		Programmable controller, relay		
Output method	-		NPN output		
Power voltage	-		10 to 28 VDC		
Load voltage	24 VDC	10 to 30 VDC	30 VDC or less		
Load current	5 to 20mA (Note 1)	5 to 20mA (Note 1)	50mA or less		
Current consumption	-	-	(When turned ON) 10mA or less with 24 VDC		
Internal voltage drop	4V or less		0.5V or less		
Light	Yellow LED (ON lighting)				
Leakage current	1mA or less		$10\mu A$ or less		
Lead wire length (standard)	Standard 1m (oil resistant vinyl cabtire code 2 conductor 0.15mm ²)		Standard 1m (oil resistant vinyl cabtire code 3 conductor 0.15mm ²)		
Maximum shock resistance	294m/s ²	980m/s ²			
Insulation resistance	20M Ω and over with 500 VDC megger				
Withstand voltage	No failure at 1000 VAC for one minute.				
Ambient temperature	-10 to + 60°C				
Protective structure	IEC standards IP67, JIS C 0920 (water tight type), oil resistance				

Note 1:Max. load current 29mA is the value at 25 °C.

The current will be lower than 20mA if ambient temperature around switch is higher than 20mA.
(5 to 10mA at 60°C)

Cylinder weight table

Stroke length (mm)	5		10		15		20		25		30		(g)
Bore size (mm)	W/o switch	With switch	Weight per 1 switch										
φ6	27	29	30	32	32	34	35	37	38	40	41	43	10
φ8	29	32	34	37	39	42	44	47	48	51	53	56	
φ12	35	45	43	53	52	62	61	71	70	80	79	89	
φ16	54	70	66	82	79	95	92	108	104	120	117	133	

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Small compact cylinder
Space saving structure

MSD-K Series

How to order

● Without switch

MSD-K - 6 - 5 - R

● With switch

MSD-KL - 6 - 5 - F0H - R - R

A Model no.

B Bore size

C Stroke length

D Switch model no.

Note 1
Note 2

E Switch quantity

F Piping port position

Note 3

Symbol	Descriptions	
A Model no.		
MSD-K	Double acting high load type Without switch	
MSD-KL	With switch	

B Bore size (mm)	
6	φ6
8	φ8
12	φ12
16	φ16

C Stroke length (mm)	
5	5
10	10
15	15
20	20
25	25
30	30

D Switch model no.				
Axial lead wire	Radial lead wire	Contact	Indicator	Lead wire
F0H*	F0V*	Reed	1 color indicator type	2-wire
F2H*	F2V*	Proximity		
F3H*	F3V*			3-wire
*Lead wire length				
Blank	3	1m (standard)		
		3m (option)		

E Switch quantity	
R	1 on rod end
H	1 on head end
D	Two

F Piping port position	
Blank	Body side surface port
R	Rear common port



Cautions on model no. selection

Note 1: For 6, 8 mm bore cylinders with reed switches, use mounting bolts that do not contain magnetic substances (stainless steel etc.).

Note 2: For 6, 8 mm bore cylinders with proximity switches, use mounting bolts that do not contain magnetic substances (stainless steel etc.).

For 12, 16 mm bore cylinders, if used with through bolts, use mounting bolts that do not contain magnetic substances (stainless steel etc.).

Note 3: For rear common port type, a side installation is possible. In this case, two bolts are used for head or rod side installation.

<Example of model number>

MSD-KL-6-5-F0H-R-R

- A Model no. : Double acting high load with switch
- B Bore size : φ 6mm
- C Stroke length : 5mm
- D Switch model no. : Reed F0H
- E Switch quantity : 1 on rod end
- F Option : Rear common port

How to order switch

SW - F0H


↓

Switch model no.
(Item D above)


Switch selection table

Switches could not be installed depending on relations between cylinder installation and stroke length.
Refer to the table below to select a switch.


All switches can be used when side installation. (Refer to page 1066 for min. stroke length with switch)



(R) Rod end installation



(H) Head end installation



Side installation

● Rod end installation

Bore size (mm)	Stroke length (mm)	Reed switch				Proximity switch			
		F0H		F0V		F2H/F3H		F2V/F3V	
		Switch installation position	R	H	R	H	R	H	R
$\phi 6$	5	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	15 to	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>
$\phi 8$	5	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	15 to	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>
$\phi 12$	5	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	15 to	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>
$\phi 16$	5	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	15 to	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>

● Head end installation

Bore size (mm)	Stroke length (mm)	Reed switch				Proximity switch			
		F0H		F0V		F2H/F3H		F2V/F3V	
		Switch installation position	R	H	R	H	R	H	R
$\phi 6$	5	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	15 to	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
$\phi 8$	5	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	15 to	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
$\phi 12$	5	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	15 to	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
$\phi 16$	5	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	10	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>
	15 to	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input checked="" type="radio"/>	<input type="radio"/>	<input type="radio"/>	<input type="radio"/>

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending


Small compact cylinder
Space saving structure

MSD-K Series


Internal structure and parts list

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

● MSD-K-6, 8, 12




● MSD-KL-6, 8, 12




No.	Parts name	Material	Remarks	No.	Parts name	Material	Remarks
1	Piston	Stainless steel		7	Piston packing seal	Nitrile rubber	
2	Bush	Oil impregnated copper alloy		8	Wear ring	Acetar resin	
3	Hexagon socket head set screw	Stainless steel		9	Magnet	Plastic	
4	Rod packing seal	Nitrile rubber		10	Adaptor	Aluminum alloy	
5	Rod bushing	Stainless steel		11	Cushion rubber H	Urethane rubber	
6	Cushion rubber R	Urethane rubber		12	Body	Aluminum alloy	Hard alumite

Internal structure and parts list

● MSD-K-16



● MSD-KL-16



No.	Parts name	Material	Remarks	No.	Parts name	Material	Remarks
1	Piston	Stainless steel		7	Piston packing seal	Nitrile rubber	
2	Bush	Oil impregnated copper alloy		8	Wear ring	Acetar resin	
3	Hexagon socket head set screw	Stainless steel		9	Magnet	Plastic	
4	Rod packing seal	Nitrile rubber		10	Adaptor	Aluminum alloy	
5	Rod bushing	Stainless steel		11	Cushion rubber H	Urethane rubber	
6	Cushion rubber R	Urethane rubber		12	Body	Aluminum alloy	Hard alumite

SCP*2
 CMK2
 CMA2
 SCM
 SCG
 SCA2
 SCS
 CKV2
 CA/OV2
 SSD
 CAT
 MDC2
 MVC
 SMD2
MSD*
 FC*
 STK
 ULK*
 JSK/M2
 JSG
 JSC3
 USSD
 USC
 JSB3
 LMB
 STG
 STS/L
 LCS
 LCG
 LCM
 LCT
 LCY
 STR2
 UCA2
 HCM
 HCA
 SRL2
 SRG
 SRM
 SRT
 MRL2
 MRG2
 SM-25
 CAC3
 UCAC
 RCC2
 MFC
 SHC
 GLC
 Ending

Small compact cylinder
 Space saving structure



MSD-K Series

Dimensions





SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

● MSD-K (L)-6, 8, 12



● MSD-K (L)-6, 8, 12-*R (rear common port)




Bore size (mm)	Without switch		With switch		Without switch/common dimension with switch											
	A	B	A	B	C	D	EE	EF	F	GA	GB	HH	I	J	K	KA
φ6	22.5	19.5	27.5	24.5	7.5	4	M3	M3	19	3	8.5	M3 depth 3	3.2	Spot face φ6.1 depth 3.5	22.5	M4 depth 6
φ8	24	21	29	26	9	4	M3	M3	21	4.5	8.5	M3 depth 3	3.2	Spot face φ6.1 depth 3.5	25	M4 depth 6
φ12	25.5	22	30.5	27	11.5	5	M5	M3	25	4	10.5	M3 depth 3	3.2	Spot face φ6.1 depth 3.5	31	M4 depth 6

Bore size (mm)	Without switch/common dimension with switch				
	KK	M	MM	N	X
φ6	M2.5 depth 4	3.5	4	11	3
φ8	M3 depth 5	4.5	5	12.5	3
φ12	M3 depth 6	5	6	15.5	3.5


Dimensions



● MSD-K (L)-16



● MSD-K (L)-16-*R (rear common port)




SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Small compact cylinder
Space saving structure

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Switch installation position

● MSD-KL-6/8 switch installation position




● MSD-KL-6/8 switch installation position dimension

(mm)

Model	Bore size (mm)	Reed switch				Proximity switch			
		F0H		F0V		F2H/F3H		F2V/F3V	
		RD	HD	RD	HD	RD	HD	RD	HD
MSD-KL	φ6	6.0	0	6.0	0	10.0	3.5	10.0	3.5
	φ8	8.5	0	8.5	0	12.5	2.5	12.5	2.5

Switch installation position

● MSD-KL-12/16 switch installation position



● MSD-KL-12/16 switch installation position dimension

(mm)

Model	Bore size (mm)	Reed switch				Proximity switch			
		F0H		F0V		F2H/F3H		F2V/F3V	
		RD	HD	RD	HD	RD	HD	RD	HD
MSD-L	$\phi 12$	9.0	0	9.0	0	13.0	3.5	13.0	3.5
	$\phi 16$	14.0	0	14.0	0	17.5	3.5	17.5	3.5

Small compact cylinder
Space saving structure

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2



Small compact cylinder, double acting fine speed type

Single rod type **MSD-F** Series

● Bore size: $\phi 6, \phi 8$

High load type **MSD-KF** Series

● Bore size: $\phi 6, \phi 8, \phi 12, \phi 16$

JIS symbol

Double acting



Specifications

Descriptions		MSD-F/MSD-LF (with switch)		MSD-KF/MSD-KLF (with switch)					
Bore size	mm	$\phi 6$	$\phi 8$	$\phi 6$	$\phi 8$	$\phi 12$	$\phi 16$		
Actuation	Double acting single rod type								
Working fluid	Compressed air								
Max. working pressure	MPa		1.0						
Min. working pressure	MPa	0.15		0.15		0.1			
Withstanding pressure	MPa		1.6						
Ambient temperature	°C	5 to 60							
Port size	Body side surface port	M3		M3	M5				
	Rear common port	-		-	M3				
Stroke tolerance	mm	$+0.5$ 0		$+2.0$ 0					
Working piston speed	mm/s	1 to 200							
Cushion		None		Rubber cushioned					
Lubrication		Must be oil free							
Allowable energy absorption	J	Non-cushion type cannot absorb an external force generated by a load installed on the cylinder. Use this with loadless, select a cushioned type, or provide an external shock.			0.004	0.014	0.044		
							0.110		

Stroke length

Bore size (mm)	Standard stroke length (mm)	Max. stroke length (mm)	Min. stroke length with 2 switches (mm)		Min. stroke length with 1 switch (mm)	
			Reed switch	Proximity switch	Reed switch	Proximity switch
$\phi 6$	5, 10, 15, 20, 25, 30	30	10	5	5	5
$\phi 8$	5, 10, 15, 20, 25, 30	30	10	5	5	5
$\phi 12$	5, 10, 15, 20, 25, 30	30	10	5	5	5
$\phi 16$	5, 10, 15, 20, 25, 30	30	10	5	5	5

Note: Other than standard stroke length is not available.

Switch specifications

Descriptions	Reed 2 wire		Proximity 2 wire		Proximity 3 wire	
	F0H/V	F2H/V	F3H/V			
Applications	Programmable controller		Programmable controller, relay			
Output method	-		NPN output			
Power voltage	-		10 to 28 VDC			
Load voltage	24 VDC		10 to 30 VDC		30 VDC or less	
Load current	5 to 20mA (Note 1)		5 to 20mA (Note 1)		50mA or less	
Current consumption	-		(When turned ON) 10mA or less with 24 VDC			
Internal voltage drop	4V or less		0.5V or less			
Light	Yellow LED (ON lighting)					
Leakage current	1mA or less		10 μ A or less			
Ending	Lead wire length (standard)		Standard 1m (oil resistant vinyl cabtire code 2 conductor 0.15mm ²)		Standard 1m (oil resistant vinyl cabtire code 3 conductor 0.15mm ²)	
Maximum shock resistance	294m/s ²		980m/s ²			
Insulation resistance	20M Ω and over with 500 VDC megger					
Withstand voltage	No failure at 1000 VAC for one minute.					
Ambient temperature	-10 to + 60 °C					
Protective structure	IEC standards IP67, JIS C 0920 (water tight type), oil resistance					

Note 1:Max. load current 29mA is the value at 25 °C.

The current will be lower than 20mA if ambient temperature around switch is higher than 20mA.

(5 to 10mA at 60°C)

Dimensions


It is the same as double acting single rod type MSD series or double acting high load type MSD-K Series. Refer to Pages1053, 1072 and 1073.

How to order

● Without switch



● With switch

**A** Model no.**B** Bore size**C** Stroke length**D** Switch model no.

Note 1

Note 2

* indicates lead wire length.

E Switch quantity**F** Piping port position

Note 3

A Model no.	Double acting single rod type MSD		Double acting high load type MSD-K			
B Bore size (mm)						
6	φ6	●	●			
8	φ8	●	●			
12	φ12		●			
16	φ16		●			
C Stroke length (mm)						
5	5	●	●			
10	10	●	●			
15	15	●	●			
20	20	●	●			
25	25	●	●			
30	30	●	●			
D Switch model no.						
Axial lead wire	Radial lead wire	Contact	Indicator	Leadwire		
F0H*	F0V*	Reed	1 color	2-wire	●	●
F2H*	F2V*		Proximity	indicator type	●	●
F3H*	F3V*			3-wire	●	●
*Lead wire length						
Blank	1m (standard)		●	●		
3	3m (option)		●	●		
E Switch quantity						
R	1 on rod end		●	●		
H	1 on head end		●	●		
D	Two		●	●		
F Piping port position						
	Bore size (φ)	All bore sizes	6	8	12	16
Blank	Body side surface port	●	●	●	●	●
R	Rear common port		●	●	●	●

⚠ Cautions on model no. selection

Note 1: For 6, 8 mm bore cylinders with reed switches, use mounting bolts that do not contain magnetic substances (stainless steel etc.).

Note 2: For 6, 8 mm bore cylinders with proximity switches, use mounting bolts that do not contain magnetic substances (stainless steel etc.).

For 12, 16 mm bore cylinders, if used with through bolts, use mounting bolts that do not contain magnetic substances (stainless steel etc.).

Note 3: For rear common port type, a side installation is possible. In this case, two bolts are used for head or rod side installation.


<Example of model number>

MSD-KLF-12-10-F0H-R-R

Model: Small compact cylinder fine speed type

- A** Model no. : Double acting high load type
- B** Bore size : φ 12mm
- C** Stroke length : 10mm
- D** Switch model no. : Reed switch F0H, lead wire 1m
- E** Switch quantity : 1 on rod end
- F** Piping port position : Rear common port

How to order switch

Switch model no.
(Item **D** above)



Small guided compact cylinder
Double acting guided type/with switch

MSDG-L Series

● Bore size: ϕ 6, ϕ 8, ϕ 12, ϕ 16



Specifications

Descriptions		MSDG-L (with switch)			
Bore size	mm	ϕ 6	ϕ 8	ϕ 12	ϕ 16
Actuation	Double acting				
Working fluid	Compressed air				
Max. working pressure	MPa		1.0		
Min. working pressure	MPa	0.2	0.15	0.1	
Withstanding pressure	MPa		1.6		
Ambient temperature	°C		5 to 60		
Connection	Body side surface port	M3		M5	
Port size	Rear common port	M3		M3	
Stroke tolerance	mm		+2.0 0		
Working piston speed	mm/s		50 to 500		
Lubrication		Not required (when lubricating, use turbine oil ISO VG32.)			

Stroke length

Bore size (mm)	Standard stroke length (mm)	Max. stroke length (mm)	Min. stroke length with 2 switches (mm)		Min. stroke length with 1 switch (mm)	
			Reed switch	Proximity switch	Reed switch	Proximity switch
ϕ 6	5, 10, 15, 20, 25, 30	30	10	5	5	5
ϕ 8	5, 10, 15, 20, 25, 30	30	10	5	5	5
ϕ 12	5, 10, 15, 20, 25, 30	30	10	5	5	5
ϕ 16	5, 10, 15, 20, 25, 30	30	10	5	5	5

Note: Other than standard stroke length is not available.

Switch specifications

Descriptions	Reed 2 wire	Proximity 2 wire	Proximity 3 wire		
	F0H/V	F2H/V	F3H/V		
Applications	Programmable controller				
Output method	-				
Power voltage	-				
Load voltage	24 VDC	10 to 30 VDC	30 VDC or less		
Load current	5 to 20mA (Note 1)	5 to 20mA (Note 1)	50mA or less		
Current consumption	-	-	(When turned ON) 10mA or less with 24 VDC		
Internal voltage drop	4V or less				
Light	Yellow LED (ON lighting)				
Leakage current	1mA or less				
Lead wire length (standard)	Standard 1m (oil resistant vinyl cabtire code 2 conductor 0.15mm ²)				
Maximum shock resistance	294m/s ²	980m/s ²			
Insulation resistance	20M Ω and over with 500 VDC megger				
Withstand voltage	No failure at 1000 VAC for one minute.				
Ambient temperature	-10 to + 60°C				
Protective structure	IEC standards IP67, JIS C 0920 (water tight type), oil resistance				

Note 1:Max. load current 29mA is the value at 25 °C.

The current will be lower than 20mA if ambient temperature around switch is higher than 20mA.
(5 to 10mA at 60°C)

Cylinder weight table

Stroke length (mm)	5	10	15	20	25	30	Weight per 1 switch (g)
Bore size (mm)							
φ6	43	48	52	57	61	66	10
φ8	50	56	63	69	76	82	
φ12	76	88	100	112	124	136	
φ16	129	146	163	180	197	214	

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Small compact cylinder
Space saving structure

MSDG-L Series

How to order

● With switch

MSDG-L - 6 - 30 - F0H - D - R

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2

SSD
CAT
MDC2
MVC
SMD2

MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3

USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT

LCY
STR2

UCA2
HCM
HCA
SRL2

SRG
SRM
SRT

MRL2
MRG2
SM-25
CAC3

UCAC
RCC2

MFC
SHC
GLC

Ending

Double acting
guided type

A Bore size

Symbol	Descriptions
A Bore size (mm)	
6	ϕ 6
8	ϕ 8
12	ϕ 12
16	ϕ 16

B Stroke length

Symbol	Descriptions
B Stroke length (mm)	
5	5
10	10
15	15
20	20
25	25
30	30

C Switch model no.

Note 1
Note 2

D Switch model no.

Axial lead wire	Radial lead wire	Contact	Indicator	Lead wire
F0H*	F0V*	Reed	1 color indicator type	2-wire
F2H*	F2V*	Proximity		
F3H*	F3V*			3-wire

*Lead wire length

Blank	1m (standard)
3	3m (option)

D Switch quantity

R	1 on rod end
H	1 on head end
D	Two

E Piping port position

Blank	Body side surface port
R	Rear common port

⚠ Note on model no. selection

Note 1: For 6, 8 mm bore cylinders with reed switches, use mounting bolts that do not contain magnetic substances (stainless steel etc.).

Note 2: For 6, 8 mm bore cylinders with proximity switches, use mounting bolts that do not contain magnetic substances (stainless steel etc.).

For 12, 16 mm bore cylinders, if used with through bolts, use mounting bolts that do not contain magnetic substances (stainless steel etc.).

Note 3: For rear common port type, a side installation is possible.

<Example of model number>

MSDG-L-6-30-F0H-D-R

A Bore size : ϕ 6mm

B Stroke length : 30mm

C Switch model no. : Reed F0H

D Switch quantity : Two

E Option : Rear common port

How to order switch


SW - F0H

Switch model no.
(Item **D** above)


Switch selection table

Switches could not be installed depending on relations between cylinder installation and stroke length.
Refer to the table below to select a switch.

All switches can be used when side installation. (Refer to page 1076 for min. stroke length with switch)



(H) Head end installation



Side installation

● Head end installation

Bore size (mm)	Stroke length (mm)	Reed switch				Proximity switch			
		F0H		F0V		F2H/F3H		F2V/F3V	
		Switch installation position	R	Switch installation position	H	Switch installation position	R	Switch installation position	H
$\phi 6$	5	X	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>	X	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>
	10	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>	X	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>
	15 to	<input type="circle"/>	<input type="circle"/>						
$\phi 8$	5	X	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>	X	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>
	10	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>	X	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>
	15 to	<input type="circle"/>	<input type="circle"/>						
$\phi 12$	5	X	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>	X	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>
	10	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>	X	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>
	15 to	<input type="circle"/>	<input type="circle"/>						
$\phi 16$	5	X	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>	X	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>
	10	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>	X	<input type="circle"/>	<input type="circle"/>	<input type="circle"/>
	15 to	<input type="circle"/>	<input type="circle"/>						

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Small compact cylinder
Space saving structure

MSDG-L Series

Internal structure and parts list

SCP*2

CMK2

CMA2

SCM

SCG

SCA2

SCS

CKV2

CA/OV2

SSD

CAT

MDC2

MVC

SMD2

MSD*

FC*

STK

ULK*

JSK/M2

JSG

JSC3

USSD

USC

JSB3

LMB

STG

STS/L

LCS

LCG

LCM

LCT

LCY

STR2

UCA2

HCM

HCA

SRL2

SRG

SRM

SRT

MRL2

MRG2

SM-25

CAC3

UCAC

RCC2


MFC

SHC


GLC

Ending

● MSDG-L-6, 8, 12



● MSDG-L-16




No.	Parts name	Material	Remarks	No.	Parts name	Material	Remarks
1	Piston	Stainless steel		10	Adaptor	Aluminum alloy	
2	Bush	Oil impregnated copper alloy		11	Cushion rubber H	Urethane rubber	
3	Hexagon socket head set screw	Stainless steel		12	Body	Aluminum alloy	Alumite
4	Rod packing seal	Nitrile rubber		13	Floating bolt	Steel	Nickeling
5	Rod bushing	Stainless steel		14	Floating bush	Stainless steel	
6	Cushion rubber R	Urethane rubber		15	Table	Aluminum alloy	Alumite
7	Piston packing seal	Nitrile rubber		16	Hexagon socket head cap bolt	Stainless steel	
8	Wear ring	Acetar resin		17	High precision guide	Stainless steel	
9	Magnet	Plastic		18	Bolt	Stainless steel	

MSDG-L Series


Dimensions



● MSDG-L-6, 8, 12



● MSDG-L-6, 8, 12-*R (rear common port)




Symbol Bore size (mm)	A	B	C	D	EE	EF	F	FF	GA	GB	H	HH	I	J	K	KA	KB	KC
φ6	33.5	24.5	7.5	4	M3	M3	18.8	19	3	8.5	27.8	M3 depth 3	3.2	Spot face φ6.1 depth 3.5	22.5	M4 depth 6	M3 depth 4	M3 (penetrating)
φ8	35	26	9	4	M3	M3	20.8	21	4.5	8.5	29.8	M3 depth 3	3.2	Spot face φ6.1 depth 3.5	25	M4 depth 6	M3 depth 4	M3 (penetrating)
φ12	38	27	11.5	5	M5	M3	24.8	25	4	10.5	36.3	M3 depth 3	3.2	Spot face φ6.1 depth 3.5	31	M4 depth 6	M3 depth 4.5	M3 (penetrating)

Symbol Bore size (mm)	L	MM	N	O	P	Q	R	SA	SB	SC	SD	SE	SF	T	U	X
φ6	32	4	11	14	27	6	9.5	12	8	3.3	5	15	9.3	5.5	5	9
φ8	33.5	5	12.5	14	29	6	10	14	8	3.3	5	15	10.3	5.5	5	9
φ12	36.5	6	15.5	19	35	6.5	13	15.5	12	4.5	5	15	12.3	7	6.5	11


Dimensions



● MSDG-L-16



● MSDG-L-16-* R (rear common port)



SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Small compact cylinder
Space saving structure

MSDG-L Series

SCP*2

CMK2

CMA2

SCM

SCG

SCA2

SCS

CKV2

CA/OV2

SSD

CAT

MDC2

MVC

SMD2

MSD*

FC*

STK

ULK*

JSK/M2

JSG

JSC3

USSD

USC

JSB3

LMB

STG

STS/L

LCS

LCG

LCM

LCT

LCY

STR2

UCA2

HCM

HCA

SRL2

SRG

SRM

SRT

MRL2

MRG2

SM-25

CAC3

UCAC

RCC2

MFC


SHC

GLC

Ending

Switch installation position

● MSDG-L-6/8 installation position




● MSDG-L-6/8 switch installation position dimension

(mm)

Model	Bore size (mm)	Reed switch				Proximity switch			
		F0H		F0V		F2H/F3H		F2V/F3V	
		RD	HD	RD	HD	RD	HD	RD	HD
MSDG	φ6	6.0	0	6.0	0	10.0	3.5	10.0	3.5
	φ8	8.5	0	8.5	0	12.5	2.5	12.5	2.5

Switch installation position

● MSDG-L-12/16 installation position




● MSDG-L-12/16 switch installation position dimension

(mm)

Model	Bore size (mm)	Reed switch				Proximity switch			
		F0H		F0V		F2H/F3H		F2V/F3V	
		RD	HD	RD	HD	RD	HD	RD	HD
MSDG	$\phi 12$	9.0	0	9.0	0	13.0	3.5	13.0	3.5
	$\phi 16$	14.0	0	14.0	0	17.5	3.5	17.5	3.5

SCP*2
 CMK2
 CMA2
 SCM
 SCG
 SCA2
 SCS
 CKV2
 CA/OV2
 SSD
 CAT
 MDC2
 MVC
 SMD2
MSD*
 FC*
 STK
 ULK*
 JSK/M2
 JSG
 JSC3
 USSD
 USC
 JSB3
 LMB
 STG
 STS/L
 LCS
 LCG
 LCM
 LCT
 LCY
 STR2
 UCA2
 HCM
 HCA
 SRL2
 SRG
 SRM
 SRT
 MRL2
 MRG2
 SM-25
 CAC3
 UCAC
 RCC2
 MFC
 SHC
 GLC
 Ending

Small compact cylinder
 Space saving structure



Small guided compact cylinder
Double acting guided fine speed types/with switch

MSDG-LF Series

● Bore size: ϕ 12, ϕ 16



Specifications

Descriptions		MSDG-LF	
Bore size	mm	ϕ 12	ϕ 16
Actuation		Double acting guided type	
Working fluid		Compressed air	
Max. working pressure	MPa	1.0	
Min. working pressure	MPa	0.1	
Withstanding pressure	MPa	1.6	
Ambient temperature	°C	5 to 60	
ULK*	Body side surface port	M5	
JSK/M2	Rear common port	M3	
JSG	Stroke tolerance	mm	$^{+2.0}_0$
JSC3	Working piston speed	mm/s	1 to 200
USSD	Cushion	Rubber cushioned	
USC	Lubrication	Not available	
JSB3	Allowable energy absorption	J	0.044
LMB			0.110

Stroke length

Bore size (mm)	Standard stroke length (mm)	Max. stroke length (mm)	Min. stroke length with 2 switches (mm)		Min. stroke length with 1 switch (mm)	
			Reed switch	Proximity switch	Reed switch	Proximity switch
ϕ 12	5, 10, 15, 20, 25, 30	30	10	5	5	5
ϕ 16	5, 10, 15, 20, 25, 30	30	10	5	5	5

Note: Other than standard stroke length is not available.

Switch specifications


Descriptions	Reed switch		Proximity switch		
	F0H/V	F2H/V	F3H/V		
Applications	Programmable controller		Programmable controller, relay		
Output method	-		NPN output		
Power voltage	-		10 to 28 VDC		
Load voltage	24 VDC		30 VDC or less		
Load current	5 to 20mA (Note 1)		50mA or less		
Current consumption	-		(When turned ON) 10mA or less with 24 VDC		
Internal voltage drop	4V or less		0.5V or less		
Light	Yellow LED (ON lighting)				
Leakage current	1mA or less		10 μ A or less		
Lead wire length (standard)	Standard 1m (oil resistant vinyl cabtire code 2 conductor 0.15mm ²)				
Maximum shock resistance	294m/s ²	980m/s ²			
Insulation resistance	20M Ω and over with 500 VDC megger				
Withstand voltage	No failure at 1000 VAC for one minute.				
Ambient temperature	-10 to + 60°C				
Protective structure	IEC standards IP67, JIS C 0920 (water tight type), oil resistance				

Note 1: Max. load current 29mA is the value at 25 °C.

The current will be lower than 20mA if ambient temperature around switch is higher than 20mA.
(5 to 10mA at 60°C)

How to order

● With switch



Symbol	Descriptions
A Bore size (mm)	
12	φ12
16	φ16

Symbol	Descriptions
B Stroke length (mm)	
5	5
10	10
15	15
20	20
25	25
30	30

C Switch model no.						
Axial lead wire	Radial lead wire	Contact	Indicator	Lead wire		
F0H*	F0V*	Reed	1 color proximity indicator type	2-wire		
F2H*	F2V*					
F3H*	F3V*					
*Lead wire length						
Blank		1m (standard)				
3		3m (option)				

D Switch quantity	
R	1 on rod end
H	1 on head end
D	Two

E Piping port position	
Blank	Body side surface port
R	Rear common port

**Note on model no. selection**

Note 1: For 12, 16 mm bore cylinders with proximity switches, if used with through bolts, use mounting bolts that do not contain magnetic substances (stainless steel etc.).

Note 2: For rear common port type, a side installation is possible.

<Example of model number>**MSDG-LF-12-10-F0H-R-R**

Model: Small guided compact cylinder fine speed type

- A Bore size : φ12mm
- B Stroke length : 10mm
- C Switch model no. : Reed switch F0H, lead wire 1m
- D Switch quantity : 1 on rod end
- E Piping port position : Rear common port

How to order switch**SW - F0H**Switch model no.
(Item D above)**Dimensions**

It is the same as the double acting guided type MSDG-L series. Refer to pages 1084, 1085.


SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Small compact cylinder
Space saving structure

MSD/MSDG Series

Selection guide

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending



STEP1 Working conditions confirmation

- 1. Bore size : D (mm)
- 2. Stroke length : St (mm)
- 3. Working pressure : P (MPa)
- 4. Travel time : t (s)
- 5. Cylinder operation direction : Vertical, horizontal

- 6. Load installation attitude : M1, M2, M3 direction
- 7. Load weight : m1, m2, m3 (kg)
- 8. Overhang distance : L1, L2, L3 (m)
- 9. Length from center of guide to table end : L (m)
- 10. Length of from table end to the load : A (m)

STEP2 Static moment confirmation

Allowable moment may vary depending on installation attitude of load (M1/M2/M3 directions)

Refer to the diagram below to calculate function moment.

- When installation attitude of load is only one way.

Check if the calculated value is within the range of allowable moment (Table 1).

- If installation attitude of load is more than two directions (when combined moment).

Divide the calculated values for each direction by allowable moment on (Table 1) to find moment ratio.



Check if the total of radio is less than 1.0.

Table 1 Allowable moment during traveling (N·m)

Bore size (mm)	M1	M2	M3
φ6	0.16	0.24	0.16
φ8	0.16	0.24	0.16
φ12	0.27	0.55	0.27
φ16	0.57	1.16	0.57


- Bending moment : M1

$$M1(N\cdot m) = 10 \times m1(kg) \times L1(m)$$





- Radial moment : M2

$$M2(N\cdot m) = 10 \times m2(kg) \times L2(m)$$




- Twist moment : M3

$$M3(N\cdot m) = 10 \times m3(kg) \times L3(m)$$



Bore size (mm)	Stroke length (m)					
	5	10	15	20	25	30
φ6	0.027	0.032	0.037	0.042	0.047	0.052
φ8	0.028	0.033	0.038	0.043	0.048	0.053
φ12	0.031	0.036	0.041	0.046	0.051	0.056
φ16	0.033	0.038	0.043	0.048	0.053	0.058



STEP3 Moment of inertia load confirmation

Moment of inertia load may act depending on installation attitude of load (M1/M2/M3 directions).

Refer to the diagram below to calculate moment of inertia load.

Moment of inertia load ($M1'/M3'$) is found by load mass ($m1, m2, m3$), overhang distance ($L1, L2, L3, L1', L3'$) and inertia force coefficient (G).

Find the inertia force coefficient (G) according to relations between inertia force coefficient and speed (Fig.1).

Check if the calculated value is within the range of allowable moment (Table 2).


Table 2 Allowable moment at inertia load applied (N·m)

Bore size (mm)	$M1'$	$M2'$	$M3'$
$\phi 6$	0.33	-	0.33
$\phi 8$	0.33	-	0.33
$\phi 12$	0.49	-	0.49
$\phi 16$	1.11	-	1.11


*Inertia load is not applied to M2 direction.

● Bending moment : $M1$

$$M1' = 10 \times m1 \times (L1 + G \times L1')$$




$$M1' = 10 \times m1 \times L1 \times (1 + G)$$




● Twist moment : $M3'$

$$M3' = 10 \times m3 \times (L3 + G \times L3')$$



$$M3' = 10 \times m3 \times L3 \times (1 + G)$$



$$M3' = 10 \times m2 \times G \times L2$$





Fig. 1 Relations between inertia force coefficient and speed

(Note) Calculate speed V_m according to STEP4.

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Small compact cylinder
Space saving structure

MSD/MSDG Series

Selection guide

SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

STEP4

1. Select one size larger type (bore size)
2. Decrease load moment
3. Decrease working speed

Install an external shock absorber to prevent generation of kinetic energy

NG

OK

Selection complete

STEP4

Allowable energy absorption confirmation

Find cylinder kinetic energy first.

$$E = \frac{1}{2} \times m \times V^2$$

$$V = \frac{St \times 10^{-3}}{t} \times (1 + 1.5 \times \frac{\alpha}{100})$$

$$\alpha = \frac{Fn}{F} \times 100$$

$$F = F_0 \times \frac{\mu}{100}$$

E : Kinetic energy

(J)

m : Weight of load

(kg)

V : Speed at stroke end

(m/s)

St : Stroke length

(mm)

t : Travel time

(S)

α : Load factor

(%)

Fn : Required thrust to move a work piece

(N)

F : Performing thrust

(N)

F₀ : Theoretical thrust (refer to the table 4)

(N)

μ : Thrust efficiency

(%)


Table 3 Required thrust (Fn)

Cylinder movement direction	Horizontal		Vertical	
	Thrust	Fn = 0.2 x 10 x m	Thrust	Fn = 1.2 x 10 x m

Table 4 Theoretical thrust table (F₀)

Bore size	Operating direction	Working pressure MPa										
		0.1	0.15	0.2	0.3	0.4	0.5	0.6	0.7	0.8	0.9	1.0
$\phi 6$	Push			6	8	11	14	17	20	23	25	28
	Pull			3	5	6	8	9	11	13	14	16
$\phi 8$	Push		8	10	15	20	25	30	35	40	45	50
	Pull		5	6	9	12	15	18	21	24	28	31
$\phi 12$	Push	11	17	23	34	45	57	68	79	90	102	113
	Pull	8	13	17	25	34	42	51	59	68	76	85
$\phi 16$	Push	20	30	40	60	80	100	121	141	161	181	201
	Pull	15	23	30	45	60	75	90	106	121	136	151

Fig. 2 Relations between thrust efficiency and pressure



Check if kinetic energy (E) is not greater than allowable energy absorption (E₀).


$E \leq E_0$

Table 5 Allowable energy absorption (E₀) (N·m)


Bore size (mm)	Allowable energy absorption E ₀ (J)
$\phi 6$	0.004
$\phi 8$	0.014
$\phi 12$	0.044
$\phi 16$	0.110

Table tilt (reference value)


● Tilt at Point A when M1 applied.




● MSDG-L-6




● MSDG-L-8



● MSDG-L-12



● MSDG-L-16



SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending
Small compact cylinder
Space saving structure

MSD/MSDG Series

SCP*2

CMK2

CMA2

SCM

SCG

SCA2

SCS

CKV2

CA/OV2

SSD

CAT

MDC2

MVC

SMD2

MSD*

FC*

STK

ULK*

JSK/M2

JSG

JSC3

USSD

USC

JSB3

LMB

STG

STS/L

LCS

LCG

LCM

LCT

LCY

STR2

UCA2

HCM

HCA

SRL2

SRG

SRM

SRT

MRL2

MRG2

SM-25

CAC3

UCAC

RCC2

MFC

SHC


GLC

Ending


Table tilt (reference value)

- Tilt at Point A when M2 applied.


$$M2 = F2 \times L2$$




● MSDG-L-6



● MSDG-L-8



● MSDG-L-12



● MSDG-L-16






Table tilt (reference value)

● Tilt at Point A when M3 applied.


$$M3 = F3 \times L3$$




● MSDG-L-6




● MSDG-L-8



● MSDG-L-12



● MSDG-L-16



SCP*2
CMK2
CMA2
SCM
SCG
SCA2
SCS
CKV2
CA/OV2
SSD
CAT
MDC2
MVC
SMD2
MSD*
FC*
STK
ULK*
JSK/M2
JSG
JSC3
USSD
USC
JSB3
LMB
STG
STS/L
LCS
LCG
LCM
LCT
LCY
STR2
UCA2
HCM
HCA
SRL2
SRG
SRM
SRT
MRL2
MRG2
SM-25
CAC3
UCAC
RCC2
MFC
SHC
GLC
Ending

Small compact cylinder
Space saving structure